

# Atmel®



## Atmel ARM® Core-based Embedded Microprocessors

High Performance, Power Efficient, Easy to Use



## Atmel ARM® Core-based Embedded Microprocessors

Device Name	Performance			Memory							Connectivity							
	Core	Clock Speed (MHz)*	Core Operating Voltage	SRAM (KB)	Cache Memory (KB) (Instruction/Data)	External Bus Interface	LPSPDR/SDRAM	LPDDR/DDR2	NAND		UART	SPI	TWI (I <sup>2</sup> C)	SSC (I <sup>2</sup> S)	CAN	LIN	USB Device (Full/High Speed)	USB Host (Full/High Speed)
									SLC ECC (bits)	MLC ECC (bits)								
SAMA5D35	Cortex-A5	536	1.2V	128	2x32	1	1/1	1/1	24	24	7	6	3	2	2	4	HS	2 HS
SAMA5D34	Cortex-A5	536	1.2V	128	2x32	1	1/1	1/1	24	24	5	6	3	2	2	4	HS	2 HS
SAMA5D33	Cortex-A5	536	1.2V	128	2x32	1	1/1	1/1	24	24	5	6	3	2	--	4	HS	2 HS
SAMA5D31	Cortex-A5	536	1.2V	128	2x32	1	1/1	1/1	24	24	7	6	3	2	--	4	HS	2 HS
SAM9M11	ARM926EJ-S	400	1.0V	64	2x32	2	1/1	1/1	1	--	5	6	2	2	--	4	HS	2 HS
SAM9M10	ARM926EJ-S	400	1.0V	64	2x32	2	1/1	1/1	1	--	5	6	2	2	--	4	HS	2 HS
SAM9G46	ARM926EJ-S	400	1.0V	64	2x32	2	1/1	1/1	1	--	5	6	2	2	--	4	HS	2 HS
SAM9G45	ARM926EJ-S	400	1.0V	64	2x32	2	1/1	1/1	1	--	5	6	2	2	--	4	HS	2 HS
SAM9X35	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	7	5	3	1	2	3	HS	1 HS, 1 FS
SAM9X25	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	7	6	3	1	2	4	HS	1 HS, 1 FS
SAM9G35	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	6	5	3	1	--	3	HS	1 HS, 1 FS
SAM9G25	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	7	6	3	1	--	4	HS	1 HS, 1 FS
SAM9G15	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	5	5	3	1	--	3	HS	1 HS, 1 FS
SAM9CN12	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	7	6	2	1	--	--	FS	2 FS
SAM9CN11	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	7	6	2	1	--	--	FS	2 FS
SAM9N12	ARM926EJ-S	400	1.0V	32	2x16	1	1/1	1/1	24	24	7	6	2	1	--	--	FS	2 FS
SAM9G20	ARM926EJ-S	400	1.0V	32	2x16	1	-/1	--	1	--	7	6	1	1	--	--	FS	2 FS
SAM9G10	ARM926EJ-S	266	1.2V	16	2x16	1	-/1	--	1	--	4	5	1	3	--	--	FS	2 FS
SAM9RL64	ARM926EJ-S	240	1.2V	64	2x4	1	-/1	--	1	--	5	5	2	2	--	--	HS	--
SAM9R64	ARM926EJ-S	240	1.2V	64	2x4	1	-/1	--	1	--	5	5	1	1	--	--	HS	--
SAM9263	ARM926EJ-S	200	1.08V	96	2x16	2	-/1	--	1	--	4	5	1	2	1	--	FS	2 FS
SAM9261	ARM926EJ-S	190	1.2V	160	2x16	1	-/1	--	1	--	4	5	1	3	--	--	FS	2 FS
SAM9260	ARM926EJ-S	210	1.8V	8	2x8	1	-/1	--	1	--	7	6	1	1	--	--	FS	2 FS
SAM9XE512	ARM926EJ-S	180	1.8V	32	16+8	1	-/1	--	1	--	7	6	2	1	--	--	FS	2 FS
SAM9XE256	ARM926EJ-S	180	1.8V	32	16+8	1	-/1	--	1	--	7	6	2	1	--	--	FS	2 FS
SAM9XE128	ARM926EJ-S	180	1.8V	16	16+8	1	-/1	--	1	--	5	6	2	1	--	--	FS	2 FS

\* Clock Speed: Max clock speed @ +85°C.

**Temperature Range:** -40°C to +85°C (Ambient)

**UART:** Support for RS485, ISO7816, IrDA, modem control lines and SPI on selected UARTs.

**TWI:** Two Wire Interface, interconnects components on a two-wire bus.

**SSC:** Serial Synchronous Controller, supports many serial synchronous communications protocols used in audio and telecom applications such as I2S, short or long frame sync.

**16-bit and 32-bit Timers:** Capture/Compare, Waveform generation and PWM modes.

**ECC:** Error Corrected Code controller.

					User Interface					Security		Control					Packages
10/100 Ethernet MAC	10/100/1000 EMAC w/ IEEE1588 Support	SD / eMMC	Soft Modem	Max I/O Pins	Graphic LCD	LCD Overlay	Resistive Touchscreen	Video Decoder	Camera Interface	Crypto Engine	Secure Boot	16-bit Timers	32-bit Timers	PWM Channels	10-bit ADC Channels	12-bit ADC Channels	
1	1	3	Yes	160	--	--	Yes	--	Yes	TDES/SHA AES/TRNG	Yes	--	6	4	--	12	BGA 324, 15x15, 0.8mm pitch
--	1	3	Yes	160	Yes	Yes	Yes	--	Yes	TDES/SHA AES/TRNG	Yes	--	5	4	--	12	BGA 324, 15x15, 0.8mm pitch
--	1	2	Yes	160	Yes	Yes	Yes	--	Yes	TDES/SHA AES/TRNG	Yes	--	5	4	--	12	BGA 324, 15x15, 0.8mm pitch
1	--	3	Yes	160	Yes	Yes	Yes	--	Yes	TDES/SHA AES/TRNG	Yes	--	5	4	--	12	BGA 324, 15x15, 0.8mm pitch
1	--	2	--	160	Yes	Yes	Yes	30fps, D1	Yes	TDES/SHA AES/TRNG	--	6	--	4	8	--	BGA 324, 15x15, 0.8mm pitch
1	--	2	--	160	Yes	Yes	Yes	30fps, D1	Yes	--	--	6	--	4	8	--	BGA 324, 15x15, 0.8mm pitch
1	--	2	--	160	Yes	--	Yes	--	Yes	TDES/SHA AES/TRNG	--	6	--	4	8	--	BGA 324, 15x15, 0.8mm pitch
1	--	2	--	160	Yes	--	Yes	--	Yes	--	--	6	--	4	8	--	BGA 324, 15x15, 0.8mm pitch
1	--	2	Yes	105	Yes	Yes	Yes	--	--	--	--	--	6	4	12	--	BGA 217, 15x15, 0.8mm pitch
2	--	2	Yes	105	--	--	--	--	--	--	--	--	6	4	12	--	BGA 217, 15x15, 0.8mm pitch
1	--	2	Yes	105	Yes	Yes	Yes	--	--	--	--	--	6	4	12	--	BGA 217, 15x15, 0.8mm pitch
1	--	2	Yes	105	--	--	--	--	Yes	--	--	--	6	4	12	--	BGA 217, 15x15, 0.8mm pitch BGA 247, 10x10, 0.5mm pitch
--	--	2	Yes	105	Yes	Yes	Yes	--	--	--	--	--	6	4	12	--	BGA 217, 10x10, 0.8mm pitch
--	--	--	--	105	Yes	--	Yes	--	--	SHA/AES/TRNG	Yes	--	6	4	12	--	BGA 217, 15x15, 0.8mm pitch BGA 247, 10x10, 0.5mm pitch
--	--	--	--	105	Yes	--	Yes	--	--	SHA/AES/TRNG	--	--	6	4	12	--	BGA 217, 10x10, 0.8mm pitch
--	--	1	--	105	Yes	--	Yes	--	--	--	--	--	6	4	12	--	BGA 217, 15x15, 0.8mm pitch
1	--	1	--	96	--	--	--	--	Yes	--	--	6	--	--	4	--	BGA 217, 10x10, 0.8mm pitch BGA 247, 10x10, 0.5mm pitch
--	--	1	--	96	Yes	Yes	--	--	--	--	--	3	--	--	--	--	BGA 217, 15x15, 0.8mm pitch
--	--	1	--	118	Yes	--	Yes	--	--	--	--	3	--	4	6	--	BGA 217, 10x10, 0.8mm pitch
--	--	1	--	49	--	--	--	--	--	--	--	3	--	3	3	--	BGA 144, 10x10, 0.8mm pitch
1	--	2	--	160	Yes	--	--	--	Yes	--	--	3	--	4	--	--	BGA 324, 15x15, 0.8mm pitch
--	--	1	--	96	Yes	--	--	--	--	--	--	3	--	--	--	--	BGA 217, 15x15, 0.8mm pitch
1	--	1	--	96	--	--	--	--	Yes	--	--	6	--	--	4	--	BGA 217, 15x15, 0.8mm pitch QFP 208, 28x28, 0.5mm pitch
1	--	1	--	96	--	--	--	--	Yes	--	--	6	--	--	4	--	BGA 217, 15x15, 0.8mm pitch QFP 208, 28x28, 0.5mm pitch
1	--	1	--	96	--	--	--	--	Yes	--	--	6	--	--	4	--	BGA 217, 15x15, 0.8mm pitch QFP 208, 28x28, 0.5mm pitch
1	--	1	--	96	--	--	--	--	Yes	--	--	6	--	--	4	--	BGA 217, 15x15, 0.8mm pitch QFP 208, 28x28, 0.5mm pitch

Peripheral implementation may vary among products, please consult individual product datasheet for detailed description

**Camera Interface:** For CMOS-type image sensor, ITU-R BT. 601/656 external interface, programmable frame capture rate, up to 12-bit data interface, SAV and EAV synchronization, preview path with scaler, YCbCr format.

**Soft Modem:** Partnership with Conexant. Offers a cost-effective solution for modem implementation

**Graphics LCD:** Supports STN & TFT displays, up to 16-bits per pixel in STN color mode, up to 16M colors in TFT mode.

**Video Decoder:** Hardware video decoding & image post processing : H.264, MPEG4, H.263, MPEG2, JPEG.

**eMMC™:** MLC NandFlash supported through MMC interface.

# Evaluation Kits

Ordering Code	Supported Device	
ATSAMA5D35-EK	SAMA5D35	
ATSAMA5D34-EK	SAMA5D34	
ATSAMA5D33-EK	SAMA5D33	
ATSAMA5D31-EK	SAMA5D31	
AT91SAM9M10-G45-EK	SAM9M10, SAM9G45	
AT91SAM9X35-EK	SAM9X35	
AT91SAM9X25-EK	SAM9X25	
AT91SAM9G35-EK	SAM9G35	
AT91SAM9G25-EK	SAM9G25	
AT91SAM9G15-EK	SAM9G15	
AT91SAM9CN11-EK	SAM9CN11, SAM9CN12	
AT91SAM9N12-EK	SAM9N12	
AT91SAM9G20-EK	SAM9G20	
AT91SAM9260-EK	SAM9260	
AT91SAM9G10-EK	SAM9G10	
AT91SAM9261-EK	SAM9261	
AT91SAM9263-EK	SAM9263	
AT91SAM9RL-EK	SAM9RL64, SAM9R64	
AT91SAM9XE-EK	SAM9XE128, SAM9XE256, SAM9XE512	
AT91SAM-ICE	All products	

Evaluation kits listed here are delivered with free Board Support Packages (BSP) for Linux®, Android™ and Microsoft® Windows®.

For more details



[Linux4SAM](#)



[Android4SAM](#)



[Windows4SAM](#)



**Atmel®** | Enabling Unlimited Possibilities®

Atmel Corporation 1600 Technology Drive, San Jose, CA 95110 USA T: (+1)(408) 441.0311 F: (+1)(408) 436.4200 | [www.atmel.com](http://www.atmel.com)

© 2013 Atmel Corporation. All rights reserved. / Rev: Atmel-6280M-ARM-Corebased-Embedded-MCU\_E\_A4\_032013

Atmel®, Atmel logo and combinations thereof, and others are registered trademarks or trademarks of Atmel Corporation or its subsidiaries. ARM®, ARMPowered® logo and others are the registered trademarks or trademarks of ARM Ltd. Other terms and product names may be the trademarks of others.

Disclaimer: The information in this document is provided in connection with Atmel products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Atmel products. EXCEPT AS SET FORTH IN THE ATMEL TERMS AND CONDITIONS OF SALES LOCATED ON THE ATMEL WEBSITE, ATMEL ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL ATMEL BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS AND PROFITS, BUSINESS INTERRUPTION, OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF ATMEL HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Atmel makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and products descriptions at any time without notice. Atmel does not make any commitment to update the information contained herein. Unless specifically provided otherwise, Atmel products are not suitable for, and shall not be used in, automotive applications. Atmel products are not intended, authorized, or warranted for use as components in applications intended to support or sustain life.